



Fenetex Smart Motor Programming

Pairing motor to remote:

- Select desired channel on remote.
- Power on motor.
- 1 jog and 3 beeps will happen.
- Press and hold the **(-) stop** button on 2secs, the motor will jog 2 times and beep 3 times to confirm pairing is complete.
- Press and release **up** or **down** button to confirm remote is paired with the motor on the correct channel.

Changing direction of motor:

- If motor is rotating in the wrong direction press and hold the **up and down** button together for 2 secs.
- Motor will jog to confirm change of direction.
- Press and release **up** or **down** button to confirm motor rotation change.

Setting upper limit:

- Press and hold **up** button for 1 sec until shade starts to move towards top.
- Stop shade close to upper limit, then fine tune limit by pressing and releasing **up** button until desired upper limit is reached.
- Save upper limit by pressing and holding **up and (-) stop** for 2 secs.
- Motor will confirm limit setting by jogging 2 times and beeping 3 times.

Setting lower limit:

- Press and hold **down** button for 1 sec until shade starts to move towards bottom.
- Stop shade close to lower limit, then fine tune limit by pressing and releasing **down** button until desired lower limit is reached.
- Save lower limit by pressing and holding **down and (-) stop** for 2 secs.
- Motor will confirm limit setting by jogging 2 times and beeping 3 times.

Fine tuning upper/lower limit:

- Press and hold **(-) stop** button and either **up** or **down** button depending on limit needing to be reset for 5 secs. (hold **up** for up, **down** for down).
- Go to new desired limit, press and hold **(-) stop** button and either **up** or **down** (must be the same as before) to exit program mode and confirm new limit setting.



Add new remote:

- On back of remote, remove cover and access area around battery.
- Around the battery is a **(p2)** button in the top left or right side of the battery, either button will work for this and any other **(p2)** applications.
- The remote already paired with motor will be considered remote "a", the remote to be paired will be "b" for this application.
- Press and release **(p2)** once for 1sec on "a" and a beep will sound, then press and release **(p2)** again for 1 sec on "a" another beep will sound.
- Making sure you are on the same channel and "a", press and release **(p2)** on "b" for 1 sec, motor will beep 3 times to confirm cloning.
- Repeat with all additional motors, making sure to select the same channel on each remote.

Deleting a remote:

- Press and release **(p2)** twice for 1sec on "a".
- Press and release **(p2)** once on "b", this will remove the "b" remote.

Deleting all remotes:

- On remote "a" press and release **(p2)** button, then press and release **(-) stop** button, then press and release **(p2)** button.
- Motor will beep 3 times and no transmitter will work. (This doesn't clear the limits in the motor, just deletes the remotes.)

Clearing limits:

- On remote "a" press and release **(p2)** button, then press and release **down** button, then press and release **(p2)** button.
- Motor will jog 2 times and beep 3 times.
- Limits can now be reprogrammed if necessary.